Alternating Gradient Synchrotron Department
Relativistic Heavy Ion Collider Project
BROOKHAVEN NATIONAL LABORATORY
Upton, New York 11973

Spin Note

AGS/RHIC/SN No. 028

Measurements of Helical Magnetic Fields Using Flat Rotating Coils

Wolfram Fischer

May 8, 1996

For Internal Distribution Only

Measurements of Helical Magnetic Fields Using Flat Rotating Coils

Wolfram Fischer

May 08, 1996

1 Introduction

Rotating coils are commonly used to measure the magnetic field coefficients (a_n, b_n) inside straight magnets [1]. They can also be employed to determine the multipole coefficients $(\tilde{a}_n, \tilde{b}_n)$ (cf. Ref. [2]) in helical magnets.

We use a cylindrical coordinate system (r, θ, s) where s designates the coordinate along the longitudinal magnet axis. The area of a flat rotating coil ranges from r_1 to r_2 and from s_1 to s_2. The magnetic flux through the coils is

$$\Phi(\theta) = N \int_{s_1}^{s_2} \int_{r_1}^{r_2} B_\theta(r, \theta)\ dr\ ds \tag{1}$$

where N is the number of coils windings. For rotating coils one has $\theta = \omega t$ and the induced voltage

$$U = -\frac{d\Phi}{dt} \tag{2}$$

is proportional to the angular velocity ω.

We will present formulae for the magnetic flux through a rotating coil for straight and helical magnets. Assuming the induced voltage is parameterized in terms of ordinary multipole coefficients (a_n, b_n) conversion formulas will be given to obtain the helical multipole coefficients $(\tilde{a}_n, \tilde{b}_n)$.

2 Straight Magnetic Fields

The azimuthal field in straight magnets can be expressed in multipole coefficients (a_n, b_n) as [2]

$$B_\theta = B_0 \sum_{n=0}^{\infty} \left(\frac{r}{r_0}\right)^n \left[b_n \cos\Big((n+1)\theta\Big) - a_n \sin\Big((n+1)\theta\Big)\right]. \tag{3}$$

B_0 is the main magnetic field and r_0 a reference radius. The magnetic flux (1) becomes

$$\Phi(\theta) = NB_0(s_2 - s_1) \sum_{n=0}^{\infty} K_n \left[b_n \cos\Big((n+1)\theta\Big) - a_n \sin\Big((n+1)\theta\Big)\right] \tag{4}$$

where the coefficients K_n are defined by

$$K_n = \frac{r_0}{n+1}\left[\left(\frac{r_2}{r_0}\right)^{(n+1)} - \left(\frac{r_1}{r_0}\right)^{(n+1)}\right] \tag{5}$$

and result from the integration over r in (1).

3 Helical Magnetic Fields

The azimuthal helical field can be written in terms of helical multipole coefficients $(\tilde{a}_n, \tilde{b}_n)$ (cf. Ref. [2]) as

$$B_\theta = \frac{B_0}{kr}\sum_{n=0}^{\infty} f_n I_{n+1}\Big((n+1)kr\Big)\Big[\tilde{b}_n \cos\Big((n+1)(\theta - ks)\Big) - \tilde{a}_n \sin\Big((n+1)(\theta - ks)\Big)\Big], \tag{6}$$

with

$$f_n = \frac{2^{n+1}(n+1)!}{(n+1)^{n+1}}\frac{1}{r_0^n k^n}. \tag{7}$$

Here B_0 denotes the transverse component of the main field close to the magnet axis. This field is vertical at the location $s = 0$. The magnetic flux (1) can be expressed as

$$\Phi(\theta) = NB_0\sum_{n=0}^{\infty} R_n\Big[\hat{b}_n \cos\Big((n+1)\theta\Big) - \hat{a}_n \sin\Big((n+1)\theta\Big)\Big] \tag{8}$$

with new coefficients

$$R_n = \frac{f_n}{k}\int_{r_1}^{r_2}\frac{1}{r} I_{n+1}\Big((n+1)kr\Big)\,dr. \tag{9}$$

The integral in (9) can be computed numerically. In (8) new magnetic multipole coefficients

$$\begin{aligned}\hat{a}_n &= +\tilde{a}_n T_n + \tilde{b}_n S_n,\\ \hat{b}_n &= -\tilde{a}_n S_n + \tilde{b}_n T_n.\end{aligned} \tag{10}$$

are used for which

$$\begin{aligned}S_n &= \frac{1}{(n+1)k}\Big[\cos\Big((n+1)ks_2\Big) - \cos\Big((n+1)ks_1\Big)\Big]\\ &= -\frac{2}{(n+1)k}\sin\frac{(n+1)k(s_2 - s_1)}{2}\sin\frac{(n+1)k(s_2 + s_1)}{2}\end{aligned} \tag{11}$$

and

$$T_n = \frac{1}{(n+1)k}\left[\sin\Big((n+1)ks_2\Big) - \sin\Big((n+1)ks_1\Big)\right]$$
$$= +\frac{2}{(n+1)k}\sin\frac{(n+1)k(s_2-s_1)}{2}\cos\frac{(n+1)k(s_2+s_1)}{2} \quad (12)$$

have been defined.

4 Conversion

We assume now a device that parameterizes the voltage (2) in terms of multipole coefficients (a_n, b_n) for straight magnets. If the measured magnetic field has helical symmetry, the coefficients $(\tilde{a}_n, \tilde{b}_n)$ in Eq. (8) can be derived as

$$\tilde{a}_n = \frac{K_n}{R_n}(s_2 - s_1)\cdot\frac{a_nT_n - b_nS_n}{S_n^2 + T_n^2},$$
$$\tilde{b}_n = \frac{K_n}{R_n}(s_2 - s_1)\cdot\frac{a_nS_n + b_nT_n}{S_n^2 + T_n^2}. \quad (13)$$

We consider three special cases.
(a) Measuring coil of one helical wavelength with $s_1 = s$, $s_2 = s + \lambda$.
From equations (11) and (12) we obtain

$$S_n = T_n = 0 \quad (14)$$

and with (10)

$$\hat{a} = \hat{b} = 0. \quad (15)$$

The magnetic flux (8) is therefore zero and the coefficients can not be obtained.

(b) Measuring coil of half helical wave length with $s_1 = 0$, $s_2 = \lambda/2$.
In this case one has

$$S_n = \begin{cases} -\frac{2}{(n+1)k} & \text{if } n \text{ even} \\ 0 & \text{if } n \text{ odd} \end{cases} \qquad \text{and} \qquad T_n = 0.$$

Only coefficients with n even (i.e. helical dipole, sextupole etc. coefficients) can be measured. For those we have

$$\tilde{a}_n = +\frac{K_n}{R_n}\frac{(n+1)\pi}{2}b_n,$$
$$\tilde{b}_n = -\frac{K_n}{R_n}\frac{(n+1)\pi}{2}a_n. \quad (16)$$

(c) Infinitely short measuring coil with $s_1 = s$, $s_2 = s + ds$.
Expanding (11) and (12) to first order in ds we obtain

$$\begin{aligned} S_n &= -\sin\Big((n+1)ks\Big)\,ds, \\ T_n &= +\cos\Big((n+1)ks\Big)\,ds \end{aligned} \tag{17}$$

and

$$\begin{aligned} \tilde{a} &= \frac{K_n}{R_n}\Big[+a_n\cos\Big((n+1)ks\Big) + b_n\sin\Big((n+1)ks\Big)\Big], \\ \tilde{b} &= \frac{K_n}{R_n}\Big[-a_n\sin\Big((n+1)ks\Big) + b_n\cos\Big((n+1)ks\Big)\Big]. \end{aligned} \tag{18}$$

If in addition $s = 0$, the $(\tilde{a}_n, \tilde{b}_n)$ can by obtained from the (a_n, b_n) by multiplication with K_n/R_n.

I would like to thank R. Gupta for discussions and reading the manuscript.

References

[1] P. Schmüser, "Magnetic measurements of the superconducting HERA magnets and analysis of systematic errors", DESY HERA-p 92-1 (1992).

[2] W. Fischer, "Magnetic field error coefficients for helical dipoles", RHIC/AP/83 and AGS/RHIC/SN/17 (1996).